Safety instruction

CAUTION!

Be careful with your operations. With a dangerous voltage you can suffer a dangerous electric shock when touching the wires!
Electric shock when touching the wires!

This device has left our premises in absolutely perfect condition. In order to maintain this condition and to ensure a safe operation, it is absolutely necessary for the user to follow the safety instructions and warning notes written in this manual.

Please note: Every information is subject to change without prior notice

PARDL56RGBAW
User Manual

Please read this user manual before using this product.

Features

Voltage: AC100-240V 50/60Hz

Power: 25W

144pcs(30R, 30G, 30B ,30A, 24W) intensive brightness LEDs

3CH/12CH DMX channels

1. Digital displays

1. Press 1. MENU (display ADDR): A001-A512
2. CHND (choose channel):3CH/12CH
3. SLND (choose master/slave1/slave2): NAST is master, SLV1,SLV2
4. SHND (choose effect):
   A. SOUN (sound control), press DOWN to confirm
   B. COLO (color changing. COL1 to COL31), press DOWN to confirm
   AUTO (speed SP01-SP08)
   C. FADE, gradually color changing (speed SP01-SP08)
5. MANU (manual change color) RED (0-255)
   GREEN (0-255)
   BLUE (0-255)
   AMBER (0-255)
   WHITE (0-255)
6. TEST (color test)
7. FHRS: (using time of light)

2. DMX operation

3-Channel mode

DMX channel		Function & Value
Channel 1	Brightness	0-15 black out
		16-255 from dark to bright
Channel 2	Strobe	0-15 black out
		16-255 strobe speed
Channel 3	Color+color changing auto run	0 black out
		1-120 color
		121-255 auto run and speed

12-Channel mode

DMX channel		Function & Value
Channel 1	Brightness	0-15 black out
		16-255 from dark to bright
Channel 2	Strobe	0-15 black out
		16-255 strobe speed
Channel 3	Red dimmer	0 black out
		1-255 red dimmer
Channel 4	Green dimmer	0 black out
		1-255 green dimmer
Channel 5	Blue dimmer	0 black out
		1-255 blue dimmer
Channel 6	Amber dimmer	0 black out
		1-255 amber dimmer
Channel 7	White dimmer	0 black out
		1-255 white dimmer
Channel 8	Color mixation	0-15 black out
		16-255 color mixation
Channel 9	Color mixation speed	0 black out
		1-255 color speed
Channel 10	Color change gradually	0-15 black out
		16-255 choose color change
Channel 11	Color gradually change speed	0-15 black out
		16-255 color gradually change speed
Channel 12	Sound active	0-15 black out
		16-255 controller sound active
		1-255 red dimmer